

## 6100 Series

### ALPHA AND FIXED-LANGUAGE SECURITY KEYPADS



With sleek, rounded edges and an appealing, symmetrical design, Honeywell's 6100 Series Alpha and Fixed-Language Display Security Keypads are an excellent addition to any installation. The Alpha keypad is now 20% smaller than previous versions, features a larger eight-line display, and includes VISTA® Intelligent Programming (VIP). VIP is menu-based programming for the most common features to help reduce keypad programming time and labor costs.

### FEATURES

- Attractive, sleek look
- Wide, easy-to-read matrix LCD display (Alpha only)\*
- VISTA Intelligent Programming (VIP)
  - Menu-based programming option (Alpha only)\*
  - Intuitive, menu-based user code programming (Alpha only)\*
- Single-button arming option
- Intuitive clock programming
- Icon indicators
- Four programmable function keys

Enhanced function and arming keys are great for quick set-up and customer use. The use of graphic icons and text simplifies operation and provides system status at a glance. Alpha and Fixed-Language keypads have the same family look. Models are available that offer voice, integrated RF or a hardwired zone to best meet the needs of the installer and the end-user's budget.

- Integrated 5800 transceiver (RF models)
  - Fixed-English: 16 zones
  - Alpha: Unlimited zones
- Voice annunciation (voice models)
- Integrated hardwired zone (ZN models)
- Compatible with all VISTA controls

*\*Supported by:  
VISTA-21iP or equivalents; Rev 3.16 and above  
VISTA-20P & VISTA-15P or equivalents; Rev 9.16 and above  
VISTA-10P or equivalents; Rev 4.16 and above*

### AGENCY

#### ETL Residential Fire and Burglary—All Models

##### US Standards:

- UL 985 – Household Fire Warning System Units
- UL 1023 – Household Burglar – Alarm System Units

##### Canadian Standards:

- ULC Subject C1023 – Standard for Household Burglar Alarm System Units
- CAN/ULC-S545 – Standard for Residential Fire Warning System Control Units

##### SIA Standard:

- ANSI/SIA CP-01-2010 – “Control Panel Standard – Features for False Alarm Reduction”

#### UL Commercial Burglary – 6162 and 6162V models

##### US Standards:

- UL 365 – Police Station Connected Burglar Alarm Units and Systems
- UL 609 – Local Burglar Alarm Units and Systems
- UL 1610 – Central-Station Burglar Alarm Units
- UL 1076 – Proprietary Burglar Alarm Units and Systems

##### Canadian Standards:

- CAN/ULC-S303 – Standard for Local Burglar Alarm Unit and Systems
- CAN/ULCS304 – Signal Receiving Centre and Premise Burglar Alarm Control Units

##### CE – All Models

# 6100 Series

## ALPHA AND FIXED-LANGUAGE SECURITY KEYPADS SPECIFICATIONS



	<b>6162</b>	<b>6162V</b>	<b>6162RF</b>	<b>6152</b>	<b>6152V</b>	<b>6152RF/ 6152RFFR</b>	<b>6152ZN/ 6152ZNFR</b>
<b>Physical</b>	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D	4.88" H x 6.93" W x 1.02" D
<b>Display</b>	4x16 Alpha-numeric Supertwist LCD, Backlit	4x16 Alpha-numeric Supertwist LCD, Backlit	4x16 Alpha-numeric Supertwist LCD, Backlit	Fixed-word LCD, Backlit	Fixed-word LCD, Backlit	Fixed-word LCD, Backlit	Fixed-word LCD, Backlit
<b>Sounder</b>	Speaker	Speaker	Speaker	Piezoelectric	Piezoelectric	Piezoelectric	Piezoelectric
<b>Voltage</b>	12VDC	12VDC	12VDC	12VDC	12VDC	12VDC	12VDC
<b>Current</b>	Standby 40mA Activated Transmissions 120mA	Standby 60mA Activated Transmissions 190mA	Standby 120mA Activated Transmissions 210mA	Standby 40mA Activated Transmissions 70mA	Standby 60mA Activated Transmissions 190mA	Standby 80mA Activated Transmissions 105mA	Standby 35mA Activated Transmissions 80mA
<b>Voice Annunciation</b>		Yes			Yes		
<b>Integrated 5800 Transceiver</b>			Yes Unlimited Zones			Yes 16 Zones	
<b>Integrated Hardwired Zone</b>							Yes

### ORDERING

<b>6162</b>	Custom Alpha Security Keypad
<b>6162V</b>	Voice Custom Alpha Security Keypad
<b>6162RF</b>	Custom Alpha Receiver/Security Keypad
<b>6152</b>	Fixed-English Security Keypad
<b>6152V</b>	Voice Fixed-English Security Keypad
<b>6152RF</b>	Fixed-English Receiver/Security Keypad
<b>6152ZN</b>	Fixed-English Security Keypad with Hardwired Zone
<b>6152RFFR</b>	Fixed-French Receiver/Security Keypad
<b>6152ZNFR</b>	Fixed-French Security Keypad with Hardwired Zone



**VIP programming reduces keypad programming time.**

#### For more information:

[www.honeywell.com/security](http://www.honeywell.com/security)

#### Automation and Control Solutions

Honeywell Security Products Americas

2 Corporate Center Dr. Suite 100

P.O. Box 9040

Melville, NY 11747

1.800.467.5875

[www.honeywell.com](http://www.honeywell.com)

# Honeywell

L/6100D/D

October 2013

© 2013 Honeywell International Inc.